

How to change the colour of the OLED display on the PRE32

<u>I32</u>	<ol style="list-style-type: none"> 1. Press and hold menu on the remote till menu shows up 2. Press 7528 3. Write down the original setting <table style="margin-left: 40px; border: none;"> <tr> <td>High</td> <td>R</td> <td>_____</td> <td>G</td> <td>_____</td> <td>B</td> <td>_____</td> </tr> <tr> <td>Medium</td> <td>R</td> <td>_____</td> <td>G</td> <td>_____</td> <td>B</td> <td>_____</td> </tr> <tr> <td>Low</td> <td>R</td> <td>_____</td> <td>G</td> <td>_____</td> <td>B</td> <td>_____</td> </tr> </table> 4. Change according schematic using left and right selector button 5. Use the DIM button to switch between High, Medium and Low 6. Press Select to confirm 	High	R	_____	G	_____	B	_____	Medium	R	_____	G	_____	B	_____	Low	R	_____	G	_____	B	_____
High	R	_____	G	_____	B	_____																
Medium	R	_____	G	_____	B	_____																
Low	R	_____	G	_____	B	_____																

	High			Medium			Low	
	White	Green		White	Green		White	Green
R	111	010		063	010		029	010
G	103	127		061	080		027	040
B	127	040		072	010		040	010

These colour numbers are for your guidance. Please feel free to adjust in small steps according to taste.